

*****READ & SAVE THESE INSTRUCTIONS *****
ACCESS LIGHTING
MODEL 52042
INSTALLATION & OPERATION INSTRUCTIONS

1) TOOLS AND MATERIALS REQUIRED

- ❖ Blade Screwdriver
- ❖ Star Screwdriver
- ❖ Wire Cutters
- ❖ Wiring supplies as required by Electrical Code
- ❖ Step Ladder

Attention:

Before assembling your lighting fixture, please read the following instructions. If you feel you do not have sufficient electrical experience, refer to a do-it-yourself wiring handbook or have your fixture installed by a qualified licensed electrician.

(2) GENERAL

1. To ensure the success of the installation, be sure to read these instructions thoroughly before beginning.
2. All electrical connections must be in accordance with local codes, ordinances, or the National Electrical Code. If you are unfamiliar with methods of installing electrical wiring, secure the services of a qualified licensed electrician.
3. These fixtures are intended for mounting to a standard 4" x 2 1/4" deep metal octagon outlet box. The box must be directly supported by the building structure and U.L. Recognized.
4. Before commencing with the installation, **disconnect the power by turning off the circuit breaker** or by removing the fuse at the fuse box. Turning the power off using the light switch is not sufficient to prevent electrical shock.

NOTE:

The important safeguards and instructions appearing in this manual are not meant to cover all possible conditions and situations that may occur. It must be understood that common sense, caution and care, are factors that cannot be built into any product. The person(s) caring for and operating the fixture must supply these factors.

(3) UNPACKING THE FIXTURE

On checking the contents of the box you will find;

1. Mounting Hardware Package
2. Glass Diffuser
3. Mounting Plate
4. Fixture Assembly
5. 5 x GU-10/35W/HGN/120V

(4) PREPARE THE FIXTURE

1. If you are replacing an existing fixture, disconnect and remove the old fixture. Expose the supply wiring from the outlet box.
2. Lay the un-assembled fixture on a soft surface and carefully remove all the packing material.
3. Attach the supplied **Crossbar** to the **J- box**, with the supplied **Mounting Screws**
4. Screw the supplied **Nipple** into the center of the **Crossbar**. Adjust to the required length and secure with the **Hex Nut** provided.
5. Attach the **Supply Wires** to the **Fixture Wires** in the following manner: The **Black supply wire** attaches to the **Black fixture wire** and the **White supply wire** attaches to the **White fixture wire**.
6. Attach the **Green/Ground wire** from the fixture to the **Electrical Supply Wire** or to the **Green Screw** located on the **Universal Crossbar**.
7. Secure these connections with supplied **Wire Connectors (2)** and tape these connections with **U.L Listed electrical tape**. Tuck all of the wires into the **Junction Box**.
8. Position the **Fixture Canopy** over the **Nipple** protruding from the **Crossbar**, and secure with the supplied **Thumb Nut**.
9. Insert the **GU-10 Bulbs. DO NOT EXCEED WATTAGE AS INDICATED ON WARNING LABEL.**
10. Insert a **Glass Shield** into the **Metal Ring** and place the complete unit onto the **bulb**. Secure by snapping the **Metal Ring** onto the **bulb**.
11. Restore electricity and enjoy your new lighting fixture.

CAUTION:

- **Ensure that the Fitting is Cool and Switched off, Before Changing Bulbs.**
- **Do Not use Bulbs Exceeding Maximum Wattage , As Per Caution Label.**
- **Do Not Touch the Bulbs or Protective Glass while fixture is in operation.**
- **Do not operate fixture next to combustible material.**
- **Do not use lamps without the Supplied Tempered Glass Shields**

a c c e s s

L I G H T I N G