

# access

## LIGHTING

### Read & Save these Instructions Models: 23425, 23426 Installation & Operation Instructions

#### (1) TOOLS AND MATERIALS REQUIRED

- ❖ BLADE & PHILIPS SCREW DRIVER
- ❖ ADJUSTABLE WRENCH
- ❖ STEP LADDER
- ❖ WIRE CUTTERS
- ❖ WIRING SUPPLIES AS REQUIRED BY ELECTRICAL CODE
- ❖ 1 X A-19/100W Lamp (medium base)

#### *Attention:*

Before assembling your lighting fixture, please read the following instructions. If you feel you do not have sufficient electrical experience, refer to a do-it-yourself wiring handbook or have your fixture installed by a qualified licensed electrician.

#### (2) GENERAL

1. To ensure the success of the installation, be sure to read these instructions and review the diagrams thoroughly before beginning
2. All electrical connections must be in accordance with local codes, ordinances, or the National Electrical Code. If you are unfamiliar with methods of installing electrical wiring, secure the services of a qualified licensed electrician
3. These fixtures are intended for mounting to a standard 4" x 2 1/4" deep metal octagon junction box. The box must be directly supported by the building structure and U.L. recognized.
4. Before commencing with the installation, disconnect the power by turning off the circuit breaker or by removing the fuse at the fuse box. Turning the power off using the light switch is not sufficient to prevent electrical shock.

#### NOTE:

The important safeguards and instructions appearing in this manual are not meant to cover all possible conditions and situations that may occur. It must be understood that common sense, caution and care are factors that cannot be built into any product. These factors must be supplied by the person(s) caring for and operating the fixture.

#### (3) UNPACKING THE FIXTURE

On checking the contents of the box you will find;

- ❖ Fixture Assembly
- ❖ Glass Diffuser
- ❖ Mounting Hardware Package
- ❖ U-shaped bracket

#### (4) PREPARING THE FIXTURE

Refer to figure for illustration of fixture parts and assembly.

1. If you are replacing an existing fixture, disconnect and remove the old fixture. Expose the supply wiring from the **(1) J-box**.
2. Lay the un-assembled fixture on a soft surface and carefully remove all the packing material.
3. Determine the desired length for your fixture's cable, trim and cut the cable to the desired length. If you need to adjust the length of the cable, release the **(7) Cord strain relief** first, then adjust the cable to the desired length. Reinstall the **(7) Cord strain relief**.
4. Mount the **(3) U-shaped bracket** to the **(1) J-box** with the supplied **(4) Mounting Screws**.
5. Connect the black supply wire to the black wire of the fixture, the white supply wire to the white wire of the fixture, the ground wires from the fixture to the ground wire of the **(1) J-box** with the supplied **(2) Wire connectors**, secure wire connectors with U.L. listed electrical tape (not included).
6. Position the **(8) Canopy** over the **(3) U-shaped bracket** such that the holes on the sides of the **(8) Canopy** line up with the holes in the **(3) U-shaped bracket**. Secure the **(8) Canopy** to the **(3) U-shaped bracket** with the supplied **(9) Screws**.
7. Insert bulb into socket. **DO NOT EXCEED WATTAGE AS PER CAUTION LABEL.**
8. Place the **(12) Glass diffuser** into the **(10) Fixture** and secure with the **(11) Screws**.  
Take care when assembling or disassembling the **(12) Glass diffuser** to avoid breakage of the **(12) Glass diffuser**.
9. Restore electricity and enjoy your new fixture.

#### CAUTION:

- Ensure that the Fitting is Cool and Switched off, Before Changing the Bulb.
- Do Not use Bulbs Exceeding Maximum Wattage, As Per Caution Label.
- Do Not Operate the Lighting Fixture close to any Combustible Material.

PLEASE SEE DIAGRAM ON REVERSE SIDE OF PAGE

